

TECHNICAL DATA SHEET

RUST CONVERTER

Convert Rust into Protective Chemical Barrier

PRODUCT DESCRIPTION:

RUST CONVERTER is a synthetic polymeric formula that converts existing rust into a moisture-free, black protective coating for metal surface preparation. When applied to rusted metal, it chemically converts rust into iron phosphate. Not only does it eliminate existing rust, but also it seals out moisture to prevent the possibility of future rust formation and corrosion. This easy-to-use product is the first step in providing long-term protection of steel and iron surfaces.

FEATURES AND BENEFITS

- Easy to apply
- No mixing required
- Paintable
- Prevents future rust from forming

APPLICATIONS

- Can be applied on any rusty iron or steel objects.
- Can be used on vehicles, fences and gates, iron railings, staircases, sheet metal, and trailers.
- It provides an excellent base primer for oil base and epoxy paints.

CLEANING

Clean all brushes and tools with water immediately after use.

TECHNICAL DATA

Form	: Liquid
Color	: Clear
pH	: 1.20 ± 0.05
Specific Gravity	: 1.18 g/mL
Touch Dry	: approx. 25 minutes

PACKAGING

RUST CONVERTER is available in liter and gallon.

COVERAGE

Recommended coverage:

6 – 7 m² per liter
25 – 30 m² per gallon

Note: *The coverage rates provided above are for guidance purposes only. Actual usage may vary depending on the specific substrate conditions and application methods.*

STORAGE AND HANDLING

RUST CONVERTER has a shelf life of 36 months if stored in tightly closed original containers.

PRECAUTIONS

HEALTH AND SAFETY

Gloves and facemasks should be worn. Any splashes on the skin or eyes should be washed off with clean water. In the event of prolonged irritation, seek medical advice. Use in a well-ventilated environment.

RUST CONVERTER is non-flammable.

Refer to the latest Safety Data Sheet (SDS) for comprehensive safety information on properly handling this product.

WARRANTY AND DISCLAIMERS

The information provided in this technical data sheet is based on our best knowledge and testing methods. Any product use outside of specifications or improper storage or installation voids any warranty. Users are encouraged to conduct their own testing to assess product suitability. Always consult the product's safety data sheet (SDS) for safety guidelines and follow recommended precautions. We reserve the right to update this data sheet without notice, and users should ensure they have the latest information.